

Power Your Outdoors!

With 280Wh portable power station R200 solar generator, no more worries about running out of power. Before reading the user manual, please charge your R200 by connecting it to the AC adapter and plugging into wall outlet.

What you want to know firstly

Q: What devices can R200 power?

A: Please kindly be noted this unit can only charge/power your devices that less than 300 Watts, please check out the operating power of your device before use.

Q: How long it can power to my exact device?

A: Working time = $280Wh \times 0.85 / \text{operating power of your device}$.

For your information, if the power consumption of your device was 30W, The running time will be $280Wh \times 0.85 / 30W = 7.9\text{hrs}$ (rough calculated).

Q: Can I charge this power station while supplying power at same time?

A: It supports DC, USB outputs through charging, but the 2 AC outputs won't pass while being charged, just for the safety of use.

Q: What kind of solar panel can pair R200 power station?

A: R200 can accept 13V~23V, 2.4A Max input, you only need to buy a solar panel with an output that this power station can be charged.

PRODUCT SPECIFICATIONS

Battery Type: Lithium-ion

Capacity: 280Wh

Input:

Charging Port: DC 5.5 x 2.1mm, 13V-23V, 2.4A Max

Output:

AC Output(x2): 110V, 60HZ, 300W Max

DC Output(x1): 9-12.6V, 10A Max

USB1 : 5V/3A 9V/2A Max

USB2+USB3+USB4: 5V/3.1A Max

2

Bulb Type: LED Flashlight with 3 Modes: Light, Strobe, SOS

Lifecycle: >1000 Times

Working Temperature Range: -10°C - 40°C / 14°F - 104°F

Weight: 5 lbs / 2.3 kg

Dimensions: 8.5 x 6.7 x 4.1in / 216 x 171 x 105mm

Package Included:

1 x 280Wh Portable Power Station

1 x AC Power Adapter


1 x Cigarette Lighter Adapter

1 x Car Charging Cable


1 x User Manual

PRODUCT DIAGRAM


【Front】




【Back】



【Left】



【Right】



3